


# SFX / ITX / TFX POWER SERIES


## SFX-AP300W



20 + 4 PIN exposed (350mm)\*1  
 12V P4 exposed (350mm)\*1  
 PATA exposed (350mm) + SATA(150mm)\*1  
 PATA exposed (350mm) + SATA(150mm) + FDD(150mm)\*1  
 Total : (20+4P\*1, 12V P4\*1, PATA\*2, SATA\*2, FDD\*1)

<b>AC Input</b>	115-230VAC , 8A/4A , 50-60HZ				
<b>DC Output Voltage</b>	+3.3V	+5V	+12V	-12V	+5Vsb
<b>Max Output Current</b>	12A	12A	20A	0.3A	2.5A
<b>Combined Power</b>	90W		240W	3.6W	12.5W
<b>Total Power</b>	300W				


## SFX-AP400W



20 + 4 PIN exposed (350mm)\*1  
 12V (P4/P8) exposed (350mm)\*1  
 PATA exposed (350mm) + SATA(150mm) + SATA(150mm) \*1  
 PATA exposed (350mm) + SATA(150mm) + FDD(150mm)\*1  
 PCIe 6+2P exposed (350mm)\*1  
 Total : (20+4P\*1, 12V P4/P8\*1, PCIe 6+2P\*1, PATA\*2, SATA\*3, FDD\*1)

<b>AC Input</b>	115-230VAC , 8A/4A , 50-60HZ				
<b>DC Output Voltage</b>	+3.3V	+5V	+12V	-12V	+5Vsb
<b>Max Output Current</b>	12A	12A	28A	0.3A	2.5A
<b>Combined Power</b>	90W		336W	3.6W	12.5W
<b>Total Power</b>	400W				


## ITX-AP300W



20 + 4 PIN exposed (350mm)\*1  
 12V P4 exposed (350mm)\*1  
 PATA exposed (350mm) + SATA(150mm)\*1  
 PATA exposed (350mm) + SATA(150mm) + FDD(150mm)\*1  
 Total : (20+4P\*1, 12V P4\*1, PATA\*2, SATA\*2, FDD\*1)

<b>AC Input</b>	115-230VAC , 8A/4A , 50-60HZ				
<b>DC Output Voltage</b>	+3.3V	+5V	+12V	-12V	+5Vsb
<b>Max Output Current</b>	12A	12A	20A	0.3A	2.5A
<b>Combined Power</b>	90W		240W	3.6W	12.5W
<b>Total Power</b>	300W				

## TFX-AP300W



20+4 PIN Exposed(500mm)\*1  
 12V 4P Exposed(500mm)\*1  
 PATA Exposed(400mm)+PATA(150mm)+SATA(150mm)+FDD(150mm)\*1  
 PATA Exposed(400mm)+SATA(150mm)+SATA(150mm)\*1  
 Total : (20+4\*1,P4\*1,PATA\*3,SATA\*3,FDD\*1)

<b>AC Input</b>	115-230VAC , 8A/4A , 50-60HZ				
<b>DC Output Voltage</b>	+3.3V	+5V	+12V	-12V	+5Vsb
<b>Max Output Current</b>	12A	12A	20A	0.3A	2.5A
<b>Combined Power</b>	90W		240W	3.6W	12.5W
<b>Total Power</b>	300W				