

# Champion Poker

V.400US

## 1. Dip Switch Setting:

## Connection Diagram 36+10 Pins

ITEM	CONTENT	1	2	3	4	5	6	7	8
SW1	DEMO SONG	NO	Off						
		YES	On						
	PAYOUT MODE	MANUAL		Off					
		AUTO		On					
	DOUBLE LIMIT	3000			Off				
		5000			On				
	DOUBLE POOL	300				Off			
		500				On			
	DOUBLE GAME	NO					Off	Off	
		HIGH LOW					On	Off	
		RED BLACK					Off	On	
		RED BLACK					On	On	
	STRIP GIRL	NO							Off
		YES							On
ANY TIME KEY IN	NO							Off	
	YES							On	
SW2	FIVE JOKER	NO	Off						
		YES	On						
	ROYAL FLUSH	NO		Off					
		YES		On					
	AUTO HOLD	HOLD			Off				
		DISCARD			On				
	HOPPER MODE	HOPPER				Off			
		TICKET				On			
	HAND COUNT	NO					Off		
		YES					On		
	SCORE BOX	NO						Off	
		YES						On	
	PLAY SCORE	NO							Off
		YES							On

PARTS SIDE		SOLDER SIDE
VIDEO RED	1	VIDEO GREEN
VIDEO BLUE	2	VIDEO SYNC
SPEAKER	3	GND
	4	
	5	
	6	
	7	
	8	
START	9	
HOLD 1/ LOW (BLACK)	10	
HOLD 5/ PLAY	11	
HOLD 4/ TAKE	12	
HOLD 3/ W-UP	13	
	14	
	15	
HOLD 2/ HIGH (RED)	16	
	17	
COIN A	18	KEY IN
	19	COIN C
RECORD	20	TEST
PAYOUT	21	KEY OUT
	22	HOPPER SWITCH
COIN A METER	23	
KEY IN METER	24	
	25	
COIN C METER	26	
HOPPER METER	27	
KEY OUT METER	28	
LAMP: START	29	
LAMP: HOLD 1/ LOW (BLACK)	30	
LAMP: HOLD 5/ PLAY	31	
LAMP: HOLD 4/ TAKE	32	
LAMP: HOLD 3/ W-UP	33	
LAMP: HOLD 2/ HIGH (RED)	34	
ATTENDANT	35	
GND	36	GND

## 2. System Adjust:

ITEM	CONTENT	DEFAULT
MAX PLAY	8, 10, 20, 40, 50, 100	40
MIN PLAY	1, 5, 8, 10, 20, 50	1
MIN PLAY-FEVER	1, 5, 8, 10, 20, 50	8
COIN RATE	1, 2, 4, 5, 10, 15, 20, 25, 40, 50, 60, 75, 80, 100, 200, 250, 400, 500, 1000	5
KEYIN RATE	1, 2, 4, 5, 10, 15, 20, 25, 40, 50, 60, 75, 80, 100, 200, 250, 400, 500, 1000	100
KEYOUT RATE	1, 2, 4, 5, 10, 15, 20, 25, 40, 50, 60, 75, 80, 100, 200, 250, 400, 500, 1000	1
TICKET RATE	1, 2, 4, 5, 10, 15, 20, 25, 40, 50, 60, 75, 80, 100, 200, 250, 400, 500, 1000	20
SYSTEM LIMIT	UNLIMIT, MAX PLAY * 1000	UNLIMIT
MAIN CHANCE	69%, 72%, 75%, 78%, 81%, 83%, 85%, 87%, 89%, 91%, 93%, 95%, 97%, 99%, 101%, 103%	95%
DUP CHANCE	94%, 96%, 98%, 100%	94%

PARTS SIDE		SOLDER SIDE
GND	1	GND
GND	2	GND
+ 5V	3	+ 5V
+ 5V	4	+ 5V
+12V	5	+12V
COUNTER POWER	6	
SSR	7	
	8	
	9	
GND	10	GND